




OPI-A

Adds iPod integration to factory radio for the 2005 and Up in the Q-7, A-8, A-6 (including RS6 & S6), and 2009 A-4 (RS & S)


What's in the box	Package Contents
<ol style="list-style-type: none"> 1. OPI-A Interface module 2. Interface power cable 3. iPod cable 4. Optical cable 5. Optical Bypass (for extending optical cable if needed) 6. USB cable (have the "A" connector side of the cable accessible to the passenger side of the vehicle cabin, but hidden from view). 	

Installation	Tool Image
<ol style="list-style-type: none"> 1. Open glove box and using European keys remove the CD changer in the glove box. 2. Disconnect all wiring harness from CD changer. Note: The factory CD changer must be disconnected. The OPI-A emulates a CD changer. 3. Connect fiber optic cables to the interface and connect the yellow wire from the Molex connector to constant +12volts and the black wire to vehicle ground. Plug in Molex connector into interface. Note: use the factory CD changer harness for tapping power and ground. 4. Connect the iPod cable to the interface. 5. Connect the USB cable to the interface. <p>Note: After plugging in the iPod to the iPod cable, secure the iPod in some fashion to keep it from being damaged.</p>	 <p>European radio removal keys.</p> 

8 Pin Molex wiring guide


Pin (3) Ground – Black wire
 Pin (7) +12Volt Constant Power – Yellow wire

8 Pin Molex connector image




Optical Cable Connections

OPI Plug



Use a pick tool to press the blue lock down from the side illustrated above and remove lock.

Factory Plug




On the Factory Plug, repeat previous step (Remove Lock)

Factory Plug




Lift tab up to allow the Fiber Optic Lead to slide out of the factory plug on the Output side.

Factory Plug




Insert Optical lead from the input OPI Connector into the Output Connector of the Factory Connector (↑ to ↓).

OPI Plug




Take the Optical leads that you've just removed from the output of the Factory Connector and insert in into the output of the OPI Connector

Before




After



Activating Interface

1. To activate the OPI-A press the **CD/AUX** button (1).
2. Press the upper left button (2) to select the iPod play selection menu. (Play selection, Playlist, Artist, Album, Genres, or <Extras>)
3. Use the center scroll wheel (3) to scroll through your selections, to make selection press the center scroll wheel and then press the upper left button and use the center scroll wheel to scroll up to the **Play selection** and then press the center scroll wheel again to play your selection.
4. To select a different Track use the center scroll wheel and scroll down to your song title and then press the center scroll wheel down (the new track will start to play after 5 seconds)




Note: The track list on the radio can only show 30 tracks at a time, if your playlist contains more than 30 tracks, scroll to track 31 and it will select the **[Next Page]** and another 30 track titles will display and the first track will start to play. If you have multiple pages of tracks, selecting track 32 will select **[Previous Page]** in your current playlist.

OPI-A Radio Screen Images

iPod menus radio screen images.

1. Main menu
2. Playlist menu
3. Artist menu
4. Albums menu
5. Genres menu
6. <Extras...> menu
 1. OPI Version date
 2. Radio Control – iPod controlled by radio
 3. Manual Control - iPod controlled from iPod controls
 4. Aux In - Aux audio input from an external audio source



Agreement: End user agrees to use this product in compliance with all State and Federal laws. NAV-TV Corp. would not be held liable for misuse of its product. If you do not agree, please discontinue use immediately and return product to place of purchase.